

Information technology — Universal Multiple-Octet Coded Character Set (UCS) —

Part 1:

Architecture and Basic Multilingual Plane

AMENDMENT 30: Additional Latin and other characters

1. List of new character names

Insert the following character name entries at the indicated positions in the tables of character names identified below, replacing the existing entries which read “(This position shall not be used)”.

Page 25. Table 5 - Row 02: LATIN EXTENDED-B

hex	Name
0222	LATIN CAPITAL LETTER OU
0223	LATIN SMALL LETTER OU
0224	LATIN CAPITAL LETTER Z WITH HOOK
0225	LATIN SMALL LETTER Z WITH HOOK
0226	LATIN CAPITAL LETTER A WITH DOT ABOVE
0227	LATIN SMALL LETTER A WITH DOT ABOVE
0228	LATIN CAPITAL LETTER E WITH CEDILLA
0229	LATIN SMALL LETTER E WITH CEDILLA
022A	LATIN CAPITAL LETTER O WITH DIAERESIS AND MACRON
022B	LATIN SMALL LETTER O WITH DIAERESIS AND MACRON
022C	LATIN CAPITAL LETTER O WITH TILDE AND MACRON
022D	LATIN SMALL LETTER O WITH TILDE AND MACRON
022E	LATIN CAPITAL LETTER O WITH DOT ABOVE
022F	LATIN SMALL LETTER O WITH DOT ABOVE
0230	LATIN CAPITAL LETTER O WITH DOT ABOVE AND MACRON
0231	LATIN SMALL LETTER O WITH DOT ABOVE AND MACRON
0232	LATIN CAPITAL LETTER Y WITH MACRON
0233	LATIN SMALL LETTER Y WITH MACRON

Page 27. Table 6 - Row 02: IPA (International Phonetic Alphabet) EXTENSIONS

hex	Name
02A9	LATIN SMALL LETTER FENG DIGRAPH
02AA	LATIN SMALL LETTER LS DIGRAPH
02AB	LATIN SMALL LETTER LZ DIGRAPH
02AC	LATIN LETTER BILABIAL PERCUSSIVE
02AD	LATIN LETTER BIDENTAL PERCUSSIVE

Page 29. Table 7 - Row 02: SPACING MODIFIER LETTERS

hex	Name
02DF	MODIFIER LETTER CROSS ACCENT
02EC	MODIFIER LETTER VOICING
02ED	MODIFIER LETTER UNASPIRATED
02EE	MODIFIER LETTER DOUBLE APOSTROPHE

Page 31. Table 8 - Row 03: COMBINING DIACRITICAL MARKS

hex	Name
0346	COMBINING BRIDGE ABOVE
0347	COMBINING EQUALS SIGN BELOW
0348	COMBINING DOUBLE VERTICAL LINE BELOW
0349	COMBINING LEFT ANGLE BELOW
034A	COMBINING NOT TILDE ABOVE
034B	COMBINING HOMOTHETIC ABOVE
034C	COMBINING ALMOST EQUAL TO ABOVE
034D	COMBINING LEFT RIGHT ARROW BELOW
034E	COMBINING UPWARDS ARROW BELOW
0362	COMBINING DOUBLE RIGHTWARDS ARROW BELOW

Page 35. Table 10 - Row 03: GREEK SYMBOLS AND COPTIC

hex	Name
03D7	GREEK KAI SYMBOL
03DB	GREEK SMALL LETTER STIGMA
03DD	GREEK SMALL LETTER DIGAMMA
03DF	GREEK SMALL LETTER KOPPA
03E1	GREEK SMALL LETTER SAMPI

Page 39. Table 12 - Row 04: CYRILLIC

hex	Name
0488	COMBINING CYRILLIC HUNDRED THOUSANDS SIGN
0489	COMBINING CYRILLIC MILLIONS SIGN
048C	CYRILLIC CAPITAL LETTER SEMISOFT SIGN

048D CYRILLIC SMALL LETTER SEMISOFT SIGN
048E CYRILLIC CAPITAL LETTER ER WITH TICK
048F CYRILLIC SMALL LETTER ER WITH TICK
04EC CYRILLIC CAPITAL LETTER E WITH DIAERESIS
04ED CYRILLIC SMALL LETTER E WITH DIAERESIS

Page 85. Table 35 - Row 20: GENERAL PUNCTUATION

hex Name
204A TIRONIAN SIGN ET
204B REVERSED PILCROW SIGN
204C BLACK LEFTWARDS BULLET
204D BLACK RIGHTWARDS BULLET

Page 87. Table 36 - Row 20: SUPERSCRIPTS AND SUBSCRIPTS, CURRENCY SYMBOLS

hex Name
20AE TUGRIK SIGN
20AF DRACHMA SIGN

Page 91. Table 38 - Row 21: LETTERLIKE SYMBOLS, NUMBER FORMS

hex Name
213A ROTATED CAPITAL Q
2183 ROMAN NUMERAL REVERSED ONE HUNDRED

Page 109. Table 47 - Row 26: MISCELLANEOUS SYMBOLS

hex Name
2619 REVERSED ROTATED FLORAL HEART BULLET

Page 261. Table 123 - Row FF: SPECIALS

hex Name
FFF9 INTERLINEAR ANNOTATION ANCHOR
FFFA INTERLINEAR ANNOTATION SEPARATOR
FFFB INTERLINEAR ANNOTATION TERMINATOR

2. List of new graphic symbols

Insert the following character graphic symbols at the indicated positions in the tables of character glyphs identified below, replacing the existing entries which are indicated by a hatched fill.

Page 24.

Table 5 - Row 02: LATIN EXTENDED-B

0222:	8
0223:	8
0224:	Z
0225:	z
0226:	À
0227:	à
0228:	Ě
0229:	ě
022A:	Ö
022B:	ö
022C:	Ō
022D:	ō
022E:	Ò
022F:	ò
0230:	Õ

0231:	$\bar{\text{O}}$
0232:	$\bar{\text{Y}}$
0233:	$\bar{y}$

Page 26.

Table 6 - Row 02: IPA (International Phonetic Alphabet) EXTENSIONS

02A9:	ƒŋ
02AA:	ls
02AB:	lz
02AC:	W W
02AD:	ꞤꞤ

Page 28.

Table 7 - Row 02: SPACING MODIFIER LETTERS

02DF:	x
02EC:	v
02ED:	=
02EE:	”

Page 30.

Table 8 - Row 03: COMBINING DIA-CRITICAL MARKS

0346:	
0347:	
0348:	
0349:	
034A:	
034B:	
034C:	
034D:	
034E:	
0362:	

Page 34.

Table 10 - Row 03: GREEK SYMBOLS AND COPTIC

03D7:	𐤇
03DB:	𐤋
03DD:	𐤍

03DF:	
03E1:	


Page 38.

Table 12 - Row 04: CYRILLIC

0488:	
0489:	
048C:	
048D:	
048E:	
048F:	
04EC:	
04ED:	

Page 84.

Table 35 - Row 20: GENERAL PUNCTUATION

204A:	
204B:	
204C:	

204D:	
-------	--

Page 86.

Table 36 - Row 20: SUPERSCRIPTS AND SUBSCRIPTS, CURRENCY SYMBOLS

20AE:	
20AF:	

Page 90.

Table 38 - Row 21: LETTERLIKE SYMBOLS, NUMBER FORMS

213A:	
2183:	

Page 108.

Table 47 - Row 26: MISCELLANEOUS SYMBOLS

2619:	
-------	--

Page 260.

Table 123 - Row FF: SPECIALS

FFF9:	
FFFA:	

FFFB:



3. Other changes

Page 23. Table 4 - Row 01: LATIN EXTENDED-B

Add a space and an asterisk next to the following character name:

hex	Name
01A6	LATIN LETTER YR *

Page 27. Table 6 - Row 02: IPA (International Phonetic Alphabet) EXTENSIONS

Add a space and an asterisk next to the following character name:

hex	Name
0280	LATIN LETTER SMALL CAPITAL R *

Page 701. Annex B

In B.1, List of all combining characters, after the entry 0486 COMBINING CYRILLIC PSILI PNEUMATA insert new entries, as shown below:

0488	COMBINING CYRILLIC HUNDRED THOUSANDS SIGN
0489	COMBINING CYRILLIC MILLIONS SIGN

Page 708. Annex D

After clause D.3 (see Amd. 29) insert the following new clause:

D.4 Interlinear annotation characters

The following characters are used to indicate that an identified character string (the annotation string) is regarded as providing an annotation for another identified character string (the base string).

INTERLINEAR ANNOTATION ANCHOR (FFF9):
This character indicates the beginning of the base string.

INTERLINEAR ANNOTATION SEPARATOR (FFFA):
This character indicates the end of the base string and the beginning of the annotation string

INTERLINEAR ANNOTATION TERMINATOR (FFFB): This character indicates the end of the annotation string.

The relationship between the annotation string and the base string is defined by agreement between the user of the originating device and the user of the receiving device. For example, if the base string is rendered in a visible form the annotation string may be rendered on a different line from the base string, in a position close to the base string.

If the interlinear annotation characters are filtered out during processing, then all characters between the Interlinear Annotation Separator and the Interlinear Annotation Terminator should also be filtered out.

Pages 709 ff. Annex E Alphabetically sorted list of character names

Insert each of the character name entries from Item 1 above at the appropriate position, ordered alphabetically by the character name, in the list of character names in Annex E.

204C	BLACK LEFTWARDS BULLET
204D	BLACK RIGHTWARDS BULLET
034C	COMBINING ALMOST EQUAL TO ABOVE
0346	COMBINING BRIDGE ABOVE
0488	COMBINING CYRILLIC HUNDRED THOUSANDS SIGN
0489	COMBINING CYRILLIC MILLIONS SIGN
0362	COMBINING DOUBLE RIGHTWARDS ARROW BELOW
0348	COMBINING DOUBLE VERTICAL LINE BELOW
0347	COMBINING EQUALS SIGN BELOW
034B	COMBINING HOMOTHETIC ABOVE
0349	COMBINING LEFT ANGLE BELOW
034D	COMBINING LEFT RIGHT ARROW BELOW
034A	COMBINING NOT TILDE ABOVE
034E	COMBINING UPWARDS ARROW BELOW
04EC	CYRILLIC CAPITAL LETTER E WITH DIAERESIS
048E	CYRILLIC CAPITAL LETTER ER WITH TICK
048C	CYRILLIC CAPITAL LETTER SEMISOFT SIGN
04ED	CYRILLIC SMALL LETTER E WITH DIAERESIS
048F	CYRILLIC SMALL LETTER ER WITH TICK
048D	CYRILLIC SMALL LETTER SEMISOFT SIGN
20AF	DRACHMA SIGN
03D7	GREEK KAI SYMBOL
03DD	GREEK SMALL LETTER DIGAMMA
03DF	GREEK SMALL LETTER KOPPA
03E1	GREEK SMALL LETTER SAMPI
03DB	GREEK SMALL LETTER STIGMA
FFF9	INTERLINEAR ANNOTATION ANCHOR
FFFA	INTERLINEAR ANNOTATION SEPARATOR
FFFB	INTERLINEAR ANNOTATION TERMINATOR
0226	LATIN CAPITAL LETTER A WITH DOT ABOVE
0228	LATIN CAPITAL LETTER E WITH CEDILLA
022A	LATIN CAPITAL LETTER O WITH DIAERESIS AND MACRON
022E	LATIN CAPITAL LETTER O WITH DOT ABOVE
0230	LATIN CAPITAL LETTER O WITH DOT ABOVE AND MACRON
022C	LATIN CAPITAL LETTER O WITH TILDE AND MACRON
0222	LATIN CAPITAL LETTER OU
0232	LATIN CAPITAL LETTER Y WITH MACRON
0224	LATIN CAPITAL LETTER Z WITH HOOK
02AD	LATIN LETTER BIDENTAL PERCUSSIVE
02AC	LATIN LETTER BILABIAL PERCUSSIVE
0227	LATIN SMALL LETTER A WITH DOT ABOVE
0229	LATIN SMALL LETTER E WITH CEDILLA
02A9	LATIN SMALL LETTER FENG DIGRAPH
02AA	LATIN SMALL LETTER LS DIGRAPH
02AB	LATIN SMALL LETTER LZ DIGRAPH
022B	LATIN SMALL LETTER O WITH DIAERESIS AND MACRON
022F	LATIN SMALL LETTER O WITH DOT ABOVE
0231	LATIN SMALL LETTER O WITH DOT ABOVE AND MACRON
022D	LATIN SMALL LETTER O WITH TILDE AND MACRON
0223	LATIN SMALL LETTER OU
0233	LATIN SMALL LETTER Y WITH MACRON
0225	LATIN SMALL LETTER Z WITH HOOK
02DF	MODIFIER LETTER CROSS ACCENT

02EE MODIFIER LETTER DOUBLE APOSTROPHE
 02ED MODIFIER LETTER UNASPIRATED
 02EC MODIFIER LETTER VOICING
 204B REVERSED PILCROW SIGN
 2619 REVERSED ROTATED FLORAL HEART BULLET
 2183 ROMAN NUMERAL REVERSED ONE HUNDRED
 213A ROTATED CAPITAL Q
 204A TIRONIAN SIGN ET
 20AE TUGRIK SIGN

Annex P (see Technical Corrigendum 1).

Insert the following entries in Annex P:

01A6 LATIN LETTER YR

This character is the capital letter form of:

0280 LATIN LETTER SMALL CAPITAL R.

0280 LATIN LETTER SMALL CAPITAL R

This character is the small letter form of:

01A6 LATIN LETTER YR.